CITA Smart 11



Home & Office Charging Solution

CITA Smart 11 commercial charger provides fast charging to an electric vehicle, using the chargers on-board three phase supply. CITA Smart 11 designed with a type 2 charging socket, the charger is compatible with either type 1, type 2 or GBT cable. Compliant with the industrial standards, the charger use MID certified meter to ensure accuracy and built-in RCD to secure the safety. CITA Smart 11 can be connected to a charging network with the help of CITA Charger Management System or any 3rd party CPMS. Multiple public chargers in one location can be integrated into the network with only one Internet communication connection.



Efficient Charging



11kW Maximum Power Range



Compatible with all Type 2 Charging Cables



CITA Smart EV App Operation via WiFi/4G/Ethernet



RFID Access



Connects to any CPMS supporting OCPP 1.6









Electrical Specifications



AC Nominal Input

Phases/Lines Rated Voltage Rated Current Frequency 3 phase + neutral+ PE 400VAC±10% 16A 50/60Hz

AC Nominal Output

Output Voltage Output Current Output Power 400VAC±10% 6 - 16A programmable 11kW

IEC 62196 Type 2, IP54, Locking

communication protocol)

High impact plastic

Green, Amber, Red

Yes

Yes

5 supplied

Integrated

Mode 3 (IEC 61851-1 / SAE J1772 compliant

General Specifications

Structure Design

Charging Socket Charging Mode

Housing Material LED Status Indication RFID Card/Tag RFID Card/Tag Qty. MID Approved kWh Meter 6mA DC Trip

Environmental Index

Operating Temperature Working Humidity Working Altitude IP/IK Rating Mounting Method -30°C ~ +55°C 5%~95% without condensation <2000m IP65, IK10 On a wall or on a poll

Package Information

Product Dimension Package Dimension Net Weight Gross Weight 342mm x 352mm x 132mm 435mm x 435mm x 225mm 4.90Kg 6.20Kg

General Specifications

Protection

Multiple Protection

Safety Standard

Dynamic Load Balancing Earthing Arrangements Earth Leakage Protection

Warranty

Communication

Communication Protocol Communication Method Programmable Charging Time Programmable Charging Power Mobile App Availability

Over/Under voltage protection, Overload protection, Short circuit protection, Current leakage protection, Grounding protection, Surge protection, Over/Under temperature protection EMC Directive 2014/30/EU, IEC 61851-1, IEC 61851-22, IEC 62196-2 Yes, via cloud software TT, TNS, TNCS (PME) A dedicated 30mA Type A RCD must be used on the supply circuit 3-years

OCPP 1.6 - JSON WiFi/4G/Ethernet Yes, preset from APP Yes, preset from APP Yes, Android and IOS App

CITA Connect App

You are powered by a smart application to manage all your CITA Smart EV Charger monitoring and settings from your IOS or Android mobile phone.

- Realtime operation with current control according to your needs
- Smart and schedule charging features
- Charging insights with analytics
- View charging logs, consumption and savings



Disclaimer: Information has been carefully checked and is believed to be accurate; however, no responsibility is assumed for inaccuracies. The status of the product(s) described in the data sheet may have changed since the date of publication and therefore that may be outdated without further notifications. For any further inquiries please contact our nearest sales office via e-mail to info@citaevcharger.co.uk or through phone.

www.citaevcharger.co.uk



United Kingdom (HQ)

52 Deerdykes View, Westfield Park, Cumbernauld, Glasgow, G68 9HN, United Kingdom Phone: 0800 147 CITA(2482)

United Arab Emirates

Unit 2106, Al Thanyah Fifth, HDS Tower, Cluster F, Jumeirah Lakes Towers, P.O. Box 191946, Dubai, UAE Phone: +971 4 5579828 Fax: +971 4 5579829

Disclaimer: Information has been carefully checked and is believed to be accurate; however, no responsibility is assumed for inaccuracies. The status of the product(s) described in the data sheet may have changed since the date of publication and therefore that may be outdated without further notifications. For any further inquiries please contact our nearest sales office via e-mail to info@citaevcharger.co.uk or through phone.

www.citaevcharger.co.uk